

## BATERIN LM

**BATERIN LM** - вспомогательный ферментативный препарат для золения.

**Химический состав:**

Специальные энзимы (ферменты)

**Цвет и консистенция при 20С:**

Белый порошок

**Срок хранения:**

В заводской упаковке при соответствующих условиях (т.е. при температуре от 5 до 25°C)

**BATERIN LM** можно хранить минимум 1 год со дня доставки.

**ПРЕДОХРАНЯТЬ ОТ ЖАРЫ! ХРАНИТЬ В СУХОМ И ПРОХЛАДНОМ МЕСТЕ!**

**Упаковка:**

Пластиковые мешки

Данная информация базируется на наших практических экспериментах, но не может являться гарантией результата, т.к. условия применения продукта различны. Не несем ответственности за потери и ущерб, нанесенный в результате использования продукта. Данная информация

To the best of our knowledge, this information is correct. Nevertheless it cannot be taken as a warranty for results of application, due to different conditions during use, and does not discharge the user from making his own controls. We cannot accept liability for any loss, injury or damage that may result from its use.

Edition 07/04

BATERIN LM

## Свойства и характеристики

- **BATERIN LM** улучшает раскрываемость структуры шкуры и разрывает протеогликановые и гликопротеиновые связи
- Уменьшает необходимое количество используемых сульфидов и ускоряет процесс золениа
- Использование **BATERIN LM** дает чистые гладкие зеленые шкуры и кожи с превосходным лицом
- Увеличивает разрыхленность шкуры и облегчает удаление гнейста и натуральных пигментов с голья

## Использование

Рекомендуется использование **BATERIN LM** в начале процесса золениа со сжиганием волоса или вместе с последней подачей извести в процессе золениа с сохранением волоса. Всегда подается непосредственно в обрабатывающую ванну (без предварительного растворения).

Может использоваться в начале процесса повторного золениа.

**BATERIN LM** активен в диапазоне рН от 7-13. Количество, которое должно быть использовано, зависит от артикула и обычно лежит в пределах от 0,05-0,2% (от веса парного сырья).

## Безопасность и экологичность.

Информация указана на листе безопасности, прилагаемом к продукту.

To the best of our knowledge, this information is correct. Nevertheless it cannot be taken as a warranty for results of application, due to different conditions during use, and does not discharge the user from making his own controls. We cannot accept liability for any loss, injury or damage that may result from its use.

Edition 07/04

BATERIN LM